

# GRACE

## DIGITAL INC.



REMOTE CONTROL CODES for the GDI-IRDT200. Please note the GDI-IRDT200 Internet Radio Tuner must have service pack v257-a-865-a-410-a-041 (available November 9, 2010) and above for the extended commands to work.

### HEADER

```
name lirc.txt
bits          16
flags SPACE_ENC|CONST_LENGTH
eps          30
aeps        100
header       9163 4397
one          664 1594
zero        664  465
ptrail       656
repeat      9159 2155
pre_data_bits 16
pre_data     0x10EF
gap         108447
toggle_bit   0
```

### STANDARD CODES

POWER	0xD02F
PRESET_1	0x807F
PRESET_2	0x40BF
PRESET_3	0xC03F
PRESET_4	0x20DF
PRESET_5	0xA05F
PRESET_6	0x609F
PRESET_7	0xE01F
PRESET_8	0x10EF
PRESET_9	0x906F
PRESET_10	0x00FF

## STANDARD CODES CONTINUED

EXTEND_PRESET	0xE817
STORE_PRESET	0x08F7
RECALL_PRESET	0xF20D
SELECT	0x7887
BACK	0xB847
RC_UP	0x48B7
RC_DOWN	0xC837
PLAY_PAUSE	0x708F
STOP	0x38C7
SKIP_NEXT	0x28D7
SKIP_PREVIOUS	0xA857
MUTE	0x50AF
VOL_UP	0x827D
VOL_DOWN	0x42BD
REPLY	0x8877
AUDIO_SOURCE	0x18E7
POWER_ON	0x51AE

## EXTENDED CODES

POWER_OFF	0x52AD
SHIFT	0x53AC
PLAYBACK_MODE	0x54AB
BROWSE_QUEUE	0x55AA
ALARM	0x56A9
SLEEP_TIMER	0x57A8
SNOOZE	0x58A7
SWITCH_MODE_TO_IRADIO	0x59A6
SWITCH_MODE_TO_MEDIA_PLAYER	0x5AA5
SWITCH_MODE_TO_FM	0x5BA4
FM_STEREO_MONO_SWITCH	0x5CA3
SEEK_DOWN	0x5DA2
SEEK_UP	0x5EA1
PRESET_MENU	0x5FA0
SHUFFLE	0x619E
REPEAT	0x629D
FORWARD	0x639C
INFO	0x649B
EQ	0x659A
MENU_TOP	0x6699
DYNAMIC_1	0x6798 # Pandora menu
DYNAMIC_2	0x6897 # Sirius menu
DYNAMIC_3	0x6996 # Live365 menu